

Features and Benefits

ANTRONIX®

MVRAM901B-G2 1.2 GHz Midsplit MoCA Enhanced VoIP Residential Amplifier

With MoCA (Multimedia over Coax Alliance) having widespread deployment for high speed in-home networking, this amplifier has enhanced performance in the MoCA band to optimize the data rates for video sharing, multi-room DVR service, video conferencing and other MoCA applications. The amplifier has four amplified output ports and a reliable passive VoIP port, which maintains RF integrity even when power is disrupted to the amplifier. The passive VoIP port provides a MoCA path to the amplified output ports to ensure full MoCA compatibility. This amplifier utilizes the Antronix patented CamPort®. This auto-seizing F-port ensures maximum contact area and reliability for multimedia applications. The amplifier can be mounted in an all-ports-down configuration which allows for ease of installation in a NID enclosure. The integrated MoCA point of entry filter prevents MoCA signals from interfering with an adjacent subscriber.



- **MoCA Enhanced**

Optimized RF performance in the MoCA band ensures maximum data rates for MoCA enabled devices. Integrated MoCA point of entry filter prevents MoCA signals from interfering with adjacent subscribers.

- **Passive VoIP Port for Critical Voice Service**

The passive VoIP port provides a passive 4.5 dB loss, even when power is disrupted to maintain critical voice service.

- **Unity Gain Forward and Return**

Active gain in the forward and return band provides unity gain in both directions for ease of installation.

- **CamPort® Auto-Seizing F-port**

Patented auto-seizing brass F-port features a "Cam Activated Mechanism" to provide full contact pressure (> 2000 grams) on the center conductor for maximum reliability.

- **All-Ports-Down Configuration for NID Enclosures**

Amplifier can be mounted with all ports facing down configuration to provide clean wiring within a NID enclosure.

- **6 kV Surge Protection**

Unique 6 kV surge protection without the use of arc gaps which may cause high impulse noise during discharge.

- **Optional Power Inserter for Remote Powering**

The amplifier can be powered remotely with a dual isolation compartment power inserter for high AC to RF isolation to prevent ingress.

- **PTC Short-Circuit Protected UL Listed Adaptor**

Self-resetting circuit provides safe protection against short-circuits to minimize maintenance costs.

Electrical Specifications

1.2 GHz Midsplit MoCA Enhanced VoIP Residential Amplifier

Forward Specifications	Frequency (MHz)	Specifications
Gain (Outputs 1–8) (dB nom)	102-1200	+0
Return Loss (dB min)	102-1200	18
Port to Port Isolation (dB min)	102-1200	22
Noise Figure (dB max)	102-1200	7
Group Delay (ns/3.58 MHz)	Ch. EIA97	30
	Ch. EIA98	15
	All Other Channels	5
Distortions¹		
Composite Triple Beat (dBc)		-74
Composite Second Order (dBc)		-62
Cross Modulation (dBc)		-74
Hum Modulation (dBc)		-80
Return Specifications	Frequency (MHz)	Specifications
Gain (Outputs 1–8) (dB nom)	5-85	+0
Return Loss (dB min)	5-85	18
Port to Port Isolation (dB min)	5-85	24
Noise Figure (dB max)	5-85	18
Group Delay (ns/1.0 MHz)	5.0-8.0	30
	8.0-83	10
	83-85	20
Distortions²		
Discrete Second Order (dBc)		-55
Discrete Third Order (dBc)		-55
Cross Modulation (dBc)		-65
MoCA Specifications	Frequency (MHz)	Specifications
Insertion Loss	1275-1400	35
Output Port to Output Port (dB max)	1400-1675	38
Isolation	1275-1400	35
Output Port to Input Port (dB min)	1400-1675	40
VoIP Port Specifications	Frequency (MHz)	Specifications
Insertion Loss (dB nom)	5-1002	4.5
	1002-1200	5.0
Return Loss (dB min)	5-1200	18

Notes:

1. +12 dBmV flat input, analog channels from 102 MHz to 550 MHz. Digital channels from 550 MHz to 1194 MHz at 6 dB below the analog channels.
2. Two +55 dBmV carriers at 13 MHz and 19 MHz.

Specifications

1.2 GHz Midsplit MoCA Enhanced VoIP Residential Amplifier

General	
Nominal Impedance	75 Ω
F-Connector Type	ANSI/SCTE 01 Brass Compliant Sealed CamPort®
Power Adaptor	15 VDC/500 mA output, UL, PTC short-circuit protected
Dimensions/Weight	5.9" W x 3.0" H x 1.5" D/0.85 lb.
Environmental	
Pressure Seal	15 psi
Surge Withstand	6 kV/3 kA Combo Wave (IEEE C62.41-1991 Cat. B3) on RF input port 6 kV/200 A Ring Wave (IEEE C62.41-1991 Cat. A3) on all RF ports
RFI Screening Effectiveness	-100 dB
Operating Temperature	-40 °C to +60 °C
Corrosion Resistance	Meets ANSI/SCTE specification

Ordering Guide

MVRAM901B/AC-G2	8 amplified outputs + 1 VoIP port amplifier. Active return. AC power adaptor included.
ARPI-2000	Optional power inserter for remote powering
ARAC-15N-50E6	AC power adaptor, 120 VAC/60 Hz Input, 15 VDC output, 500 mA, Efficiency Level VI

